

## DET-RWATER Water Detector



Thieves are not the only intruders that need to be detected in homes and business premises, and with an estimated 9.7 billion litres of water lost through domestic water leaks each year alone, this is clearly a massive problem. Early detection is vital in order to prevent costly and, in some cases, irreparable damage and the use of DET-RWATER will help reduce the financial and environmental impact of water leaks.

Each year leaks from washing machines and dishwashers, overflowing bathtubs, unsecured pipes and environmental flooding cause significant damage resulting in costly repairs to buildings and their contents. The fully supervised radio water detector, the DET-RWATER, will alert a warning to the control panel when identifying the presence of water at a chosen location and the wireless capability means you can be flexible in every environment including basements or adjacent to washing machines. Ultimately the DET-RWATER gives the homeowner or business owner the opportunity to react before the leak develops, helping to minimise damage to the property and furnishings.

## Product specification

<b>Product code</b>	DET-RWATER
<b>Transmitter Dimensions (L x W x D)</b>	90 x 35 x 30mm
<b>Sensor Dimensions (L x W x D)</b>	45 x 10 x 15mm
<b>Weight</b>	Approx. 90g
<b>Material</b>	PC-ABS
<b>Power Supply</b>	3V CR2 lithium battery
<b>Battery Service Life</b>	Up to 3 years
<b>Environmental Class</b>	I (-10°C to +55°C)
<b>Security Level</b>	2
<b>Operating Frequency</b>	868.6625 MHz
<b>Cable Length</b>	Approx. 1m

## Compatible products

<b>i-on16/ EUR</b>	16 zone control panel
<b>i-on30EX/ EXEUR</b>	30 zone control panel
<b>i-on40/ EUR</b>	40 zone control panel
<b>i-on50EX/ EXEUR</b>	50 zone control panel
<b>i-on160EX/ EXEUR</b>	160 zone control panel
<b>Multibus</b>	1000 zone control panel
<b>Menvier30KPZ</b>	30 zone control panel
<b>Menvier40KPZ</b>	40 zone control panel
<b>Menvier100KPZ</b>	100 zone control panel
<b>Menvier300KPZ</b>	300 zone control panel
<b>762rEUR-00</b>	Two channel radio receiver
<b>768rEUR-50</b>	Eight channel radio receiver expandable to 32 channels with the 769
<b>769rEUR-50</b>	Eight channel expander for use with the 768

**Eaton**  
Electrical Sector EMEA  
Route de la Longeraie 7  
1110 Morges, Switzerland

**Eaton**  
Security House,  
Vantage Point Business Village,  
Mitcheldean, Gloucestershire  
GL17 0SX

Tel: +44 (0)1594 545 400  
Fax: +44 (0)1594 545 401  
Email: [securitysales@eaton.com](mailto:securitysales@eaton.com)  
Web: [www.touchpoint-online.com](http://www.touchpoint-online.com)



Powering Business Worldwide