

PRM-UST Music source, USB, SD, Tuner PLENA solutions



- ▶ MP3 playback from SD card and USB inputs
- ▶ FM tuner with RDS, presets and digital control
- ▶ Simultaneous operation of SD/USB player and FM tuner
- ▶ Separate outputs for digital source and FM tuner

The PRM-UST is a professional multi-source music player intended to be used as background music source for public address and commercial audio applications. It has USB interface, SD card input for playing stored music files, and tuner for FM frequency band broadcast receiver. It is used in hotels, shops, supermarkets, restaurants, bars, canteens, gyms, showrooms, and other places where background music creates the right atmosphere.

Functions

USB/SD

With an SD/USB memory capacity of up to 32 GB (up to 8000 tracks) and the option to connect the USB either on the front or rear panel, the digital player provides hours of high-quality, uninterrupted music playback from a single source. It supports music organized on a SD card or USB device in multiple folders. The player will automatically search and play all supported files on a flash memory device. It can play MP3 files with bit-rates from 32 kbps to 320 kbps, mono / stereo, and both constant bit-rates (CBR) and variable bit-rate (VBR) are supported.

Tuner

The digitally controlled FM tuner can accurately capture the radio stations and has presets memory to store favorite radio stations.

Outputs

The media player (SD or USB) and the tuner can operate simultaneously on different outputs. The level of the outputs can be set with the volume control buttons on the front panel or the remote. There is a

combined output which has priority for media player, it automatically switches over to the FM tuner when there is no active media player input.

Regulatory information

Safety	EN 62368-1
Immunity	EN 55035
Emissions	EN 55032 EN 61000-3-3
Environment	EN IEC 63000

Region	Regulatory compliance/quality marks
Europe	CE
Environment	RoHS

Parts included

Quantity	Component
1	Music source PRM-UST
1	Mains power cord
1	Set of 19 inches mounting brackets with screws
1	Remote control (battery not included)

Quantity	Component
2	Stereo RCA audio cable
1	Antenna cord including connector
1	SD memory card (16 GB)
1	Quick installation guide
1	Safety information

Technical specifications

Electrical

Mains power supply

Voltage range	110–120 VAC +/-10%, 50–60 Hz 220–240 VAC +/-10%, 50–60 Hz
Power supply fuse	0.63 A / 250 V
Power consumption (W)	15 W

FM Tuner

FM frequency range	87.5 – 108 MHz
Frequency response	50 Hz – 12 kHz +/-3 dB
Channel separation (1 kHz)	>25 dB
Signal-to-noise ratio	>50 dB
FM input sensitivity	26 dBu
Antenna impedance	75 ohm
Audio output level	1.5 V rms +/-1 dB @10 kΩ

USB or SD source

Frequency response (Hz)	50 Hz – 18 kHz +/-1 dB
Signal-to-noise ratio (1kHz)	>75 dB
Total harmonic distortion (1 kHz)	<0.5%
Channel separation (1 kHz)	>70 dB
Audio output level	1.5 V rms +/-1 dB at 10 kΩ

USB output current limit	500 mA max. (front and rear USB ports together)
Memory card capacity (GB)	32 GB maximum
Supported file structure	FAT, FAT32 and exFAT
Supported audio files	mp3, wma, wav, flac, ape, m4a

Mechanical

Dimension (H x W x D) (mm) (with brackets)	44 mm x 482 mm x 250 mm
Dimension (H x W x D) (in) (with brackets)	1.73 in x 18.98 in x 9.84 in
Dimensions (H x W x D) (mm) (without brackets)	44 mm x 430 mm x 250 mm
Dimensions (H x W x D) (in) (without brackets)	1.73 in. x 16.93 in x 9.84 in.
Mounting	Stand-alone, 19" rack (19" wide, 1 U high)
Color in RAL	RAL 9017 Traffic black
Weight (kg) (unit)	3.20 kg
Remote control dimensions (L x W x D) (mm) (remote control)	130 mm x 44 mm x 20 mm
Weight (g) (remote control without batteries)	32 g

Environmental

Operating temperature (°C)	0 °C – 45 °C
Storage temperature (°C)	-40 °C – 70 °C
Operating relative humidity, non-condensing (%)	<90%

Ordering information

PRM-UST Music source, USB, SD, Tuner
 USB/SD MP3 player with FM tuner functions.
 Order number **PRM-UST | F.01U.397.942**

Represented by:

Europe, Middle East, Africa:
 Bosch Security Systems B.V.
 P.O. Box 80002
 5600 JB Eindhoven, The Netherlands
 Phone: + 31 40 2577 284
www.boschsecurity.com/xc/en/contact/
www.boschsecurity.com

Germany:
 Bosch Sicherheitssysteme GmbH
 Robert-Bosch-Ring 5
 85630 Grasbrunn
 Tel.: +49 (0)89 6290 0
 Fax: +49 (0)89 6290 1020
de.securitysystems@bosch.com
www.boschsecurity.com

North America:
 Bosch Security Systems, LLC
 130 Perinton Parkway
 Fairport, New York, 14450, USA
 Phone: +1 800 289 0096
 Fax: +1 585 223 9180
onlinehelp@us.bosch.com
www.boschsecurity.com

Asia-Pacific:
 Robert Bosch (SEA) Pte Ltd, Security Systems
 11 Bishan Street 21
 Singapore 573943
 Phone: +65 6571 2808
 Fax: +65 6571 2699
www.boschsecurity.com/xc/en/contact/
www.boschsecurity.com