

DET-RARB Radio Assistance Required Button



Suitable for doctor's surgeries, shops, schools and other commercial buildings, this radio assistance required button sounds the alert for local assistance

Flexibility is at the forefront of the design ensuring practicality in every environment. The DET-RARB can be programmed to suit the requirements of the business or end user either by activating a discreet signal by utilising log only zone types and chime, whilst programming the radio assistance required button as a HUA will provide a more urgent alert.

Product specification

Product code	DET-RARB
Dimensions (L x W x D)	85 x 85 x 52mm
Weight	Approx. 90g
Material	PC-ABS
Power Supply	3V lithium battery (size CR2450)
Battery Service Life	Approx. 24 months
Environmental Class	II (-10°C to +50°C)
Security Grade	2
Operating Frequency	868.6625 MHz
Housing Material	Thermoplastic resin

Compatible products

i-on16/ EUR	16 zone control panel
i-on30EX/ EXEUR	30 zone control panel
i-on40/ EUR	40 zone control panel
i-on50EX/ EXEUR	50 zone control panel
i-on160EX/ EXEUR	160 zone control panel
Multibus	1000 zone control panel
Menvier30KPZ	30 zone control panel
Menvier40KPZ	40 zone control panel
Menvier100KPZ	100 zone control panel
Menvier300KPZ	300 zone control panel
EXP-R10	10 zone radio expander
EXP-R30	30 zone radio expander